



A problem has occurred

2026-06-06 07:14:47

Error message:

This license has expired on 2026-05-30.

License Information:

License serial no:	3916
Licensee:	Adeona Oy
Product:	PDFReactor Web Service
Version:	12.0
License Type:	CPU
Amount:	12 Thread(s)
Maintenance Exp. Date:	2026-05-30
Expiration Date:	2026-05-30
Purchase Date:	2015-11-18
Conditions:	[This license is for use on development systems only. It may not be used on staging or productive systems of any kind.]
Sign Date:	2025-06-02 15:12



41096086

Pistorasia 1-osainen LED-hakuvalolla, ruuvil., Q.x, antrasiitti samettinen

Tuotemerkki: Hager

GTIN: 4011334381600

Sähkönumero: 2507608

SCHUKO-pistorasia LED-hakuvalolla - Korotettu kosketussuojaus - ruuviiliittimet Nimellisjännite 250 VAC Taajuus 50/60 Hz Nimellisvirta 16 A Valaistusvoimakkuus (valkoinen) 0,2 cd Tehonkulutus 0,25 W/0,35 VA Päälekytkentäkirkkaus n. 2 lx Poiskytkentäkirkkaus n. 4 lx Johtimen poikkipinta (lanka) maks. 2,5 mm² Varoitus! Tuotteet erikoisuppoasennusrungolla. LED-hakuvalolliset keskiölevyt eivät ole yhteensopivia vakioistorasiarunkojen ja keskiölevyjen kanssa. - lisäetu pistorasian ja suunnistusvalon yhdistelmällä - integroitu kirkkausanturi joka kytkee hakuvalon hämärällä ja pois kun valaistustaso on riittävä - LEDillä pitkä käyttöikä - valkoinen LED-valo - ketjutus mahdollinen, siksi ideaalinen myös jälkiasennukseen

ETIM-tiedot:

Aktiivisten kontaktien määrä (pyöreä)	2
Aktiivisten kontaktien määrä (litteä)	0
Merkinantolampulla	ei
Yksikköjen määrä	1
Moduulien lukumäärä	1
Kytettävien pistorasioiden määrä	0
Vaiheiden lukumäärä	1
Merkintä/ilmaisu	ei ole
Saranoitu kansi	ei
Parannettu kosketussuojaus	kyllä
Merkintäpaikka	ei
RAL-numero (vastaava)	7021
Läpinäkyvä	ei
Lukittava	ei
Irrutus/vapautus-mekanismi	ei
Eristetty asennus	kyllä
Toiminnanilmaisevalla valolla	ei
Hakuvalolla	kyllä
Ylijännitesuojaus	ei
Vikavirtasuojauks	ei
Pienoissulakkeella	ei
Erikoisteholähde	ei erityistä virtalähdettä
Halogeeniton	kyllä
Pintamateriaali	matta
Antibakteerinen käsittely	ei
Ketjutusmahdollisuus	ei
Päälle/pois-kytkimellä	ei
Kääntyvä keskiosa	ei
Nimellisvirta	16 A
Nimellisjännite	250 V
Taajuus	50 Hz - 60 Hz
Laitteen leveys	71 mm
Laitteen korkeus	71 mm
Apple HomeKit -yhteensopiva	ei



REALOBJECTS

PDFReactor®

Evaluation Version

This PDF document was created by an evaluation version of RealObjects PDFReactor 12.3.2 (17644). The evaluation version is fully functional, but includes this information page. It must not be used for production purposes. The information page and all other evaluation notices must not be removed from the PDF file.

NOTE: Conversions in evaluation mode might be slower and the results might have a larger file size than in production mode.

Buy PDFReactor

To buy a PDFReactor license follow this link:

[Buy PDFReactor online](#)

About PDFReactor

RealObjects PDFReactor is a powerful formatting processor for converting HTML and XML documents into PDF. It uses Cascading Style Sheets (CSS) to define page layout and styles. The server-side tool enables a great variety of applications in the fields of ERP, eCommerce and Electronic Publishing.

PDFReactor supports HTML5, CSS3 and JavaScript.

It allows you to dynamically generate PDF documents such as invoices, delivery notes and shipping documents on-the-fly. PDFReactor allows you to easily add server-based PDF generation functionality to your application or service. Since PDFReactor runs on a server, the end-user in general does not need any software other than a PDF viewer.

For more information visit www.pdfreactor.com

Amazon Alexa -yhteensopiva	ei
Google Assistant -yhteensopiva	ei
IFTTT-tuki	ei
Rankoille käyttöolosuhteille (VDE:n mukaan)	ei

Hyväksynät / merkinnät:

