



EEN100

Hämararelee pp. anduriga, 230VAC, 16A, 5-100/50-2000 Lux

Bränd: Hager

GTIN: 3250617579308

Hämararelee pp. anduriga, 230VAC, 16A, 5-100/50-2000 Lux

ETIM-teave:

Tunnuspinge	230 V
Rated frequency	50 Hz - 60 Hz
Max. incandescent lamp load	2300 W
Max. load fluorescent lamp	1000 VA
Max. load fluorescent lamp (Duo circuit)	1000 VA
Max. load fluorescent lamp (parallel compensated)	1000 VA
Max. switching current (cos phi = 0.6)	10 A
Rated switch current	10 A
Adjustment range brightness value	5 lx - 2000 lx
With programmable overnight shutoff	No
Push button input	No
Rated voltage light sensor	230 V
Protection class light sensor	II
Mounting method light sensor	Other
Mounting method	DIN rail
Width in number of modular spacings	1
Sisseehitussügavus	17.8 mm
Degree of protection (IP)	IP20
Degree of protection (IP) light sensor	IP55

Kinnitused / märgistused:

